

DOMOS WIFI PIR Sensor



Main features

- Sends alerts to your smartphone when it detects motion in the room
- Label and manage several sensors with the app
- Combine it with other DOMOS devices.
- Integrated Wi-Fi (no additional gateway required)
- Automatic Wi-Fi network settings from the free app (Android and iOS)
- Connection in two simple steps, install batteries and pair the sensor with the router through the app

Technical features

- Infrared motion sensor (PIR)
- Detection angle: 110°, 10 meters
- Integrated blue LED light (flashing during pairing and sensor trigger)
- SET button in rear panel for reset and trigger sensor
- Customizable timers for idle periods of the sensor
- History of activations
- Low battery notification (voltage<4V) and lost connection symbol in the app
- Wi-Fi: 2,4GHz, 802.11 b/g/n, WPA/WPA2 PSK
- Battery: 3xAA
- Ultra-low consumption in standby mode (Sleep mode current < 80uA)
- Max. current consumption < 250mA when transmit 802.11b, CCK 1Mbps, Pout=+19.5dBm
- Battery life time : > 4000 times WiFi access trigger
- LiMH rechargeable batteries can be used
- Operating conditions, temperature and humidity: 0-60°C, 10-99%
- Mini screwdriver included for batteries installation pilas

Logistic info

- Model code: DOM-SM-0
- EAN code: 8436545446157
- Size: 118x45x39mm
- Device net weight: 82g
- Total gift box weight: 122g
- Gift box size: 125x150x53mm
- Units/master carton: 10 pcs/ctn
- Master carton size: 280x265x200mm

Copyright TvTech S. L.

Reproduction of the content of this document in whole or part and/or its disclosure to a third party is strictly forbidden without the permission of its owner. Offenders are liable to pay for the damages. All rights reserved in the event of the grant of a patent or the registration of a utility model or design.

