

DOMOS WIFI Panic button



Características principales

- Panic button to send an alert to your smartphone when the sensor button is pushed
- Label and manage several sensors with the app
- Combine it with other DOMOS devices
- Integrated Wi-Fi (no additional gateway required)
- Automatic Wi-Fi network settings from the free app (Android and iOS)
- Connection in two simple steps, install batteries and pair the sensor with the router through the app

Technical features

- Combine it with other DOMOS devices
- Integrated blue LED light (flashing during pairing and sensor trigger)
- Customizable timers for idle periods of the sensor
- History of activations
- Low battery notification (voltage<2,6V) and lost connection symbol in the app
- Wi-Fi: 2,4GHz, 802.11 b/g/n, WPA/WPA2 PSK
- Batteries: 2xAAA
- Ultra-low consumption in standby mode (Sleep mode current < 10uA)
- Max. current consumption < 250mA when transmit 802.11b, CCK 1Mbps, Pout=+19.5dBm
- Battery life time : > 4000 times WiFi access trigger
- LiMH rechargeable batteries can be used
- Operating conditions, temperature and humidity: 0-60°C, 10-99%
- Mini screwdriver included for batteries installation

Logistic info

- Model code: DOM-BE-0
- EAN code: 8436545446133
- Size: 120x75x55mm
- Device net weight: 30g
- Total gift box weight: 96g
- Gift box size: 125x150x53mm
- Units/master carton: 10 pcs/ctn
- Master carton size: 280x265x200mm

Copyright TvTech S. L.

Reproduction of the content of this document in whole or part and/or its disclosure to a third party is strictly forbidden without the permission of its owner. Offenders are liable to pay for the damages. All rights reserved in the event of the grant of a patent or the registration of a utility model or design.

